



## PORTABLE GASOLINE GENSET

### Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

### Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utilitypower outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

### Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

### Genset

Standby	kVA	12
Prime	kVA	11
Start System	Electric Start	
Power Factor	CosΦ	1.0
Voltage	380(50HZ)	
Fuel Type	Gasoline	
Fuel Tank Capacity	lt	25

### Engine

Model	194F	
Kw (Standby/Prime)	10 / 9	
Bore / Stroke	mm	94 x 72
Number of Cylinder	1	
Displacement	cc	500
Oil Capacity	lt	1,1
Engine Type	4-Stroke, Air Cooled, OHV	

### Size

Weight	kg	110
L x W x H	cm	73 x 55 x 61